

Temporary Power Distribution

SM5 (PSOA) – PORTABLE SOCKET OUTLET ASSEMBLY, 5 X 10 AMP WITH 10 AMP PLUG



APPLICATIONS

A safe and portable socket outlet assembly (PSOA) for use on construction sites or at outdoor events.

CONSTRUCTION

- Meets requirements of AS/NZS 3012 & 3190
- 5 x 10A sockets: 250V, 50Hz, IP66, RCBO protected
- 10A industrial plug on 1.8m heavy duty lead (AS/NZS 3191)
- Supply – 10A, 230/240V – single phase + N + E
- RCBO – 2 pole 10A 230/240V
- IP65 enclosure
- 3.5kg with cable and plug
- Dimensions – 325mm (L) x 295mm (H) x 270mm (W)

PRODUCT FEATURES

- Bright, visible and safe
- Weathertight: IP65 enclosure + IP66 outlets
- Robust and rugged enclosure with durable handle
- Overall RCBO protection
- Tested and certified
- Ground clearance

Product Code	Cable Size (m)	Supply Power	Socket Outlets
SM5	1.8	10A, 230/240V – single phase + N + E	5 x 10A, 250V, 50Hz, IP66 RCBO protected

SM6 (PSOA) – PORTABLE SOCKET OUTLET ASSEMBLY, 6 X 15 AMP OUTLETS WITH 10 AMP PLUG



APPLICATIONS

Residential and light commercial building sites or at indoor/outdoor events.

CONSTRUCTION

- 6 x 15A sockets single phase 3P
- 10A industrial plug on 1.8m heavy duty lead (AS/NZS 3191)
- Frequency 50 – 60Hz
- Supply – 10A, 230V – single phase + N + E
- RCBO – 1P + N 30mA 10A 10kA
- IP44/IP65
- Specially blended polyethylene enclosure
- Meets AS/NZS 3190:2011 and AS/NZS 3012:2010
- Dimensions – 412mm (L) x 280mm (H) x 268mm (W)

PRODUCT FEATURES

- 2 Year limited warranty
- Industrial lead and plug
- Stackable for storage and transportation
- 40mm ground clearance
- Third party tested and certified
- Impact resistant robust enclosure for outdoor use
- Assembled with standard industrial sockets allowing hassle free replacement
- Customisation available on request
- Assembled with trade tested components
- Designed for NZ & AU conditions

Product Code	Cable Size (m)	Supply Power	Socket Outlets	Weight (kg)
SM6	1.8	10A, 230V – single phase + N + E	6 x 15A single phase 3P	6

Chain & Rigging has taken every precaution to ensure accurate information on this data page, but accept no liability for any errors or omissions. Chain & Rigging reserves the right to modify specifications at any time.